

## WINDING RESISTANCE METER

## **GENERAL**

It is a measurement of DC voltage and current in regard to Ohm's law, where R (resistance) is equal to V (voltage) divided by I (amps). The instrument is suitable to measure resistance of inductive products also.

## **FEATURES**

Selectable four resistance ranges.

5 digits LED display

High measurement Current (10A)

Wire True four Technique elimanates lead resistance errors Systems

Fully protected against overloads

Proven design

Computer connectivity



## **TECHNICAL SPECIFICATIONS**

PARAMETER	DESCRIPTION	
DISPLAY	5 DIGIT, LED TYPE 7 SEGMENT DISPLAY	
RANGES	0 - 9.9999 mOhm @ 10A	П
	0 - 99.999 mOhm @ 10A	
	0 - 999.99 mOhm @ 1A	
	0 - 9.9999 ohm @ 0.1A	
	0 - 99.999 ohm @ 0.01A	
	0 - 999.99 ohm @ 0.001A	
POWER	230 V AC, SINGLE PHASE, 50 Hz	
SYSTEM	4 WIRE MEASUREMENT	
WARM UP TIME	10 MIN.	

